Clean Set of Amended Claims

1. (Twice Amended) A method of establishing a communication channel between a base station and a mobile station, comprising:

(a) generating control signals and data signals within the communication channel, said control signals having a first sequence of L-bits and a second sequence of L-bits;

(b) autocorrelating the first and second sequences to generate first and second autocorrelated values;

(c) cross-correlating the first and second sequences to generate first and second cross-correlated values; and

(d) combining the first and second autocorrelated values and the first and second cross-correlated values.

34. (Amended) A frame structure for a communication system, each frame having 15 slots and each slot having N number of pilot bits, where 2≤ N≤ 16, such that there are N number of pilot bit patterns of 15 bits in the frame, wherein the improvement comprises N number of pilot bit patterns having at least one of the following pilot bit patterns:

Slot No 1 2 3 4.....15
Pilot bit pattern 1 = (1 0 0 0 1 1 1 1 0 1 0 1 1 0 0)
Pilot bit pattern 2 = (1 0 1 0 0 1 1 0 1 1 1 0 0 0 0)
Pilot bit pattern 3 = (1 1 0 0 0 1 0 0 1 1 0 1 0 1 1)
Pilot bit pattern 4 = (0 0 1 0 1 0 0 0 0 1 1 1 0 1 1)
Pilot bit pattern 5= (1 1 1 0 1 0 1 1 0 0 1 0 0 0 1)
Pilot bit pattern 6 = (1 1 0 1 1 1 0 0 0 0 1 0 1 0 0)
Pilot bit pattern 7 = (1 0 0 1 1 0 1 0 1 1 1 1 0 0 0)
Pilot bit pattern 8= (0 0 0 0 1 1 1 0 1 1 0 0 1 0 1)

35. (Amended) A frame structure for an uplink Dedicated Physical Control Channel (DPCCH) in a communication system, wherein the improvement comprises each frame of the uplink DPCCH having 15 slots and N_{pilot} number of pilot bits in each slot, where $3 \leq N_{pilot} \leq 8$ and pilot bit patterns comprise at least one of the following based on N_{pilot} number of pilot bits:

	when N_{pilot} = 5					when N_{pilot} = 6					
Bit #	0	1	2	3	4	0	1	2	3	4	5
Slot #0	1	1	1	1	0	1	1	1	1	1	0
1	0	0	1	1	0	1	0	0	1	1	0
2	0	1	1	0	1	1	0	1	1	0	1
3	0	0	1	0	0	1	0	0	1	0	0
4	1	0	1	0	1	1	1	0	1	0	1
5	1	1	1	1	0	1	1	1	1	1	0
6	1	1	1	0	0	1	1	1	1	0	0
7	1	0	1	0	0	1	1	0	1	0	0
8	0	1	1	1	0	1	0	1	1	1	0
9	1	1	1	1	1	1	1	1	1	1	1
10	0	1	1	0	1	1	0	1	1	0	1
11	1	0	1	1	1	1	1	0	1	1	1
12	1	0	1	0	0	1	1	0	1	0	0
13	0	0	1	1	1	1	0	0	1	1	1
14	0	0	1	1	1	1	0	0	1	1	1

	when N_{pilot} = 7							when N_{pilot} = 8							
Bit #	0	1	2	3	4	5	6	0	1	2	3	4	5	6	7
Slot #0	1	1	1	1	1	0	1	1	1	1	1	1	1	1	0
1	1	0	0	1	1	0	1	1	0	1	0	1	1	1	0
2	1	0	1	1	0	1	1	1	0	1	1	1	0	1	1
3	1	0	0	1	0	0	1	1	0	1	0	1	0	1	0
4	1	1	0	1	0	1	1	1	1	1	0	1	0	1	1
5	1	1	1	1	1	0	1	1	1	1	1	1	1	1	0
6	1	1	1	1	0	0	1	1	1	1	1	1	0	1	0
7	1	1	0	1	0	0	1	1	1	1	0	1	0	1	0
8	1	0	1	1	1	0	1	1	0	1	1	1	1	1	0
9	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
10	1	0	1	1	0	1	1	1	0	1	1	1	0	1	1
11	1	1	0	1	1	1	1	1	1	1	0	1	1	1	1
12	1	1	0	1	0	0	1	1	1	1	0	1	0	1	0
13	1	0	0	1	1	1	1	1	0	1	0	1	1	1	1
14	1	0	0	1	1	1	1	1	0	1	0	1	1	1	1

36. (Amended) A frame structure for a Random Access Channel (RACH) in a communication system, wherein the improvement comprises each frame of the RACH having 15 slots and N_{pilot} number of pilot bits in each slot, where N_{pilot}=8, and pilot bit patterns comprise:

	N_{pilot} = 8							
Bit #	0	1	2	3	4	5	6	7
Slot #0	1	1	1	1	1	1	1	0
1	1	0	1	0	1	1	1	0
2	1	0	1	1	1	0	1	1
3	1	0	1	0	1	0	1	0
4	1	1	1	0	1	0	1	1
5	1	1	1	1	1	1	1	0
6	1	1	1	1	1	0	1	0
7	1	1	1	0	1	0	1	0
8	1	0	1	1	1	1	1	0
9	1	1	1	1	1	1	1	1
10	1	0	1	1	1	0	1	1
11	1	1	1	0	1	1	1	1
12	1	1	1	0	1	0	1	0
13	1	0	1	0	1	1	1	1
14	1	0	1	0	1	1	1	1

37. (Amended) A frame structure for a downlink Dedicated Physical Control Channel (DPCCH) in a communication system, wherein the improvement comprises each frame of the downlink DPCCH having 15 slots and N_{pilot} number of pilot bits in each slot, where $2 \leq N_{pilot} \leq 16$, and pilot bit patterns comprise at least one of the following based on N_{pilot} number of pilot bits:

	when N_{pilot} = 2	when N_{pilot} = 4		when N_{pilot} = 8				when N_{pilot} = 16							
Symbol #	0	0	1	0	1	2	3	0	1	2	3	4	5	6	7
Slot #0	11	11	11	11	11	11	10	11	11	11	10	11	11	11	10
1	00	11	00	11	00	11	10	11	00	11	10	11	11	11	00
2	01	11	01	11	01	11	01	11	01	11	01	11	10	11	00
3	00	11	00	11	00	11	00	11	00	11	00	11	01	11	10
4	10	11	10	11	10	11	01	11	10	11	01	11	11	11	11
5	11	11	11	11	11	11	10	11	11	11	10	11	01	11	01
6	11	11	11	11	11	11	00	11	11	11	00	11	10	11	11
7	10	11	10	11	10	11	00	11	10	11	00	11	10	11	00
8	01	11	01	11	01	11	10	11	01	11	10	11	00	11	11
9	11	11	11	11	11	11	11	11	11	11	11	11	00	11	11
10	01	11	01	11	01	11	01	11	01	11	01	11	11	11	10
11	10	11	10	11	10	11	11	11	10	11	11	11	00	11	10
12	10	11	10	11	10	11	00	11	10	11	00	11	01	11	01
13	00	11	00	11	00	11	11	11	00	11	11	11	00	11	00
14	00	11	00	11	00	11	11	11	00	11	11	11	10	11	01

38. (Amended) A frame structure for a downlink Dedicated Physical Control Channel (DPCCH) using Space Time Transmit Diversity (STTD) encoding in a communication system, wherein the improvement comprises each frame of the downlink DPCCH having 15 slots and N_{pilot} number of pilot bits in each slot, where $2 \leq N_{pilot} \leq 16$, and pilot bit patterns comprise at least one of the following based on N_{pilot} number of pilot bits:

	when N_{pilot} = 4		when N_{pilot} = 8				when N_{pilot} = 16							
Symbol #	0	1	0	1	2	3	0	1	2	3	4	5	6	7
Slot #0	01	10	11	00	00	10	11	00	00	10	11	00	00	10
1	10	10	11	00	00	01	11	00	00	01	11	10	00	10
2	11	10	11	11	00	00	11	11	00	00	11	10	00	11
3	10	10	11	10	00	01	11	10	00	01	11	00	00	00
4	00	10	11	11	00	11	11	11	00	11	11	01	00	10
5	01	10	11	00	00	10	11	00	00	10	11	11	00	00
6	01	10	11	10	00	10	11	10	00	10	11	01	00	11
7	00	10	11	10	00	11	11	10	00	11	11	10	00	11
8	11	10	11	00	00	00	11	00	00	00	11	01	00	01
9	01	10	11	01	00	10	11	01	00	10	11	01	00	01
10	11	10	11	11	00	00	11	11	00	00	11	00	00	10
11	00	10	11	01	00	11	11	01	00	11	11	00	00	01
12	00	10	11	10	00	11	11	10	00	11	11	11	00	00
13	10	10	11	01	00	01	11	01	00	01	11	10	00	01
14	10	10	11	01	00	01	11	01	00	01	11	11	00	11

39. (Amended) A frame structure for a Secondary Common Control Physical Channel (S-CCPCH) in a communication system, wherein the improvement comprises each frame of the S-CCPCH having 15 slots and N_{pilot} number of pilot bits in each slot, where $8 \leq N_{pilot} \leq 16$, and pilot bit patterns comprise at least one of the following based on N_{pilot} number of pilot bits:

	when $N_{pilot} = 8$				when $N_{pilot} = 16$							
Symbol #	0	1	2	3	0	1	2	3	4	5	6	7
Slot #0	11	11	11	10	11	11	11	10	11	11	11	10
1	11	00	11	10	11	00	11	10	11	11	11	00
2	11	01	11	01	11	01	11	01	11	10	11	00
3	11	00	11	00	11	00	11	00	11	01	11	10
4	11	10	11	01	11	10	11	01	11	11	11	11
5	11	11	11	10	11	11	11	10	11	01	11	01
6	11	11	11	00	11	11	11	00	11	10	11	11
7	11	10	11	00	11	10	11	00	11	10	11	00
8	11	01	11	10	11	01	11	10	11	00	11	11
9	11	11	11	11	11	11	11	11	11	00	11	11
10	11	01	11	01	11	01	11	01	11	11	11	10
11	11	10	11	11	11	10	11	11	11	00	11	10
12	11	10	11	00	11	10	11	00	11	01	11	01
13	11	00	11	11	11	00	11	11	11	00	11	00
14	11	00	11	11	11	00	11	11	11	10	11	01

40. (Amended) A frame structure for a Secondary Common Control Physical Channel (S-CCPCH) using Space Time Transmit Diversity (STTD) encoding in a communication system, wherein the improvement comprises each frame of the S-CCPCH having 15 slots and N_{pilot} number of pilot bits in each slot, where $8 \leq N_{pilot} \leq 16$, and pilot bit patterns comprise at least one of the following based on N_{pilot} number of pilot bits:

	$N_{pilot} = 8$				$N_{pilot} = 16$							
Symbol #	0	1	2	3	0	1	2	3	4	5	6	7
Slot #0	11	00	00	10	11	00	00	10	11	00	00	10
1	11	00	00	01	11	00	00	01	11	10	00	10
2	11	11	00	00	11	11	00	00	11	10	00	11
3	11	10	00	01	11	10	00	01	11	00	00	00
4	11	11	00	11	11	11	00	11	11	01	00	10
5	11	00	00	10	11	00	00	10	11	11	00	00
6	11	10	00	10	11	10	00	10	11	01	00	11
7	11	10	00	11	11	10	00	11	11	10	00	11
8	11	00	00	00	11	00	00	00	11	01	00	01
9	11	01	00	10	11	01	00	10	11	01	00	01
10	11	11	00	00	11	11	00	00	11	00	00	10
11	11	01	00	11	11	01	00	11	11	00	00	01
12	11	10	00	11	11	10	00	11	11	11	00	00
13	11	01	00	01	11	01	00	01	11	10	00	01
14	11	01	00	01	11	01	00	01	11	11	00	11